

Hytork to Rotex Crossover List (Rotex torque at least 95% of Hytork torque)

REV 0, January 9, 2009

| Typical Air Pressure (psi) | Hytork Model | Spring End Torque (in-lb) | Lower Mounting | Upper Mounting (mm) | Rotex Model | Spring End Torque (in-lb) | Lower Mounting | Upper Mounting (mm) |
|----------------------------|--------------|---------------------------|----------------|---------------------|-------------|---------------------------|----------------|---------------------|
| 60 | XL26-S60 | 47 | F3/F5/14mm | 80X30X20 | ECV40SR-6 | 45 | F3/F5/11mm | 80X30X20 |
| 80 | XL26-S80 | 63 | F3/F5/14mm | 80X30X20 | ECV40SR-8 | 67 | F3/F5/11mm | 80X30X20 |
| 60 | XL71-S60 | 118 | F5/F7/17mm | 80X30X20 | ECV63SR-6 | 133 | F5/F7/14mm | 80X30X20 |
| 80 | XL71-S80 | 158 | F5/F7/17mm | 80X30X20 | ECV63SR-8 | 196 | F5/F7/14mm | 80X30X20 |
| 60 | XL131-S60 | 222 | F5/F7/17mm | 80X30X20 | ECV80SR-20 | 230 | F5/F7/17mm | 80X30X20 |
| 80 | XL131-S80 | 296 | F5/F7/17mm | 80X30X20 | ECV80SR-26 | 320 | F5/F7/17mm | 80X30X20 |
| 60 | XL186-S60 | 298 | F7/17mm | 80X30X20 | ECV90SR-20 | 350 | F5/F7/17mm | 80X30X20 |
| 80 | XL186-S80 | 397 | F7/17mm | 80X30X20 | ECV90SR-26 | 487 | F5/F7/17mm | 80X30X20 |
| 60 | XL221-S60 | 416 | F7/17mm | 80X30X20 | ECV100SR-20 | 495 | F7/F10/22mm | 80X30X20 |
| 80 | XL221-S80 | 555 | F7/17mm | 80X30X20 | ECV100SR-26 | 689 | F7/F10/22mm | 80X30X20 |
| 60 | XL281-S60 | 497 | F7/17mm | 80X30X20 | ECV100SR-20 | 495 | F7/F10/22mm | 80X30X20 |
| 80 | XL281-S80 | 663 | F7/17mm | 80X30X20 | ECV100SR-26 | 689 | F7/F10/22mm | 80X30X20 |
| 60 | XL426-S60 | 748 | F10/22mm | 80X30X20 | ECV125SR-20 | 840 | F7/F10/22mm | 80X30X20 |
| 80 | XL426-S80 | 997 | F10/22mm | 80X30X20 | ECV125SR-26 | 1,174 | F7/F10/22mm | 80X30X20 |
| 60 | XL681-S60 | 1,203 | F10/22mm | 80X30X20 | ECV150SR-67 | 1,430 | F10/F12/27mm | 80X30X20 |
| 80 | XL681-S80 | 1,604 | F10/22mm | 80X30X20 | ECV150SR-80 | 1,917 | F10/F12/27mm | 80X30X20 |
| 60 | XL1126-S60 | 1,968 | F12/27mm | 130X30X30 | ECV175SR-67 | 2,048 | F10/F12/27mm | 80X30X20 |
| 80 | XL1126-S80 | 2,624 | F12/27mm | 130X30X30 | ECV175SR-80 | 2,756 | F10/F12/27mm | 80X30X20 |
| 60 | XL1371-S60 | 2,424 | F12/27mm | 130X30X30 | ECV201SR-67 | 3,570 | F10/F12/27mm | 130X30X30 |
| 80 | XL1371-S80 | 3,232 | F12/27mm | 130X30X30 | ECV201SR-80 | 4,900 | F10/F12/27mm | 130X30X30 |
| 60 | XL2586-S60 | 4,576 | F16/46mm | 130X30X30 | ECV250SR-67 | 5,140 | F16/46mm | 130X30X30 |
| 80 | XL2586-S80 | 6,101 | F16/46mm | 130X30X30 | ECV250SR-80 | 6,855 | F16/46mm | 130X30X30 |
| 60 | XL4581-S60 | 8,097 | F16/46mm | 130X30X30 | ECV300SR-67 | 8,220 | F16/46mm | 130X30X30 |
| 80 | XL4581-S80 | 10,795 | F16/46mm | 130X30X30 | ECV300SR-80 | 10,957 | F16/46mm | 130X30X30 |

For reference only. Information subject to change without notice.